

Product datasheet
Characteristics

8538SCG14V02S
STARTER MOTOR CONTROL 1000VAC



Main

Product or component type	Combination Starter
Range of product	S
Control circuit	Separate control circuit

Complementary

[Uc] control circuit voltage	110 V AC 50 Hz 120 V AC 60 Hz
Motor starter type	Non reversing
Poles description	3P
Motor power hp	10 hp 460 V AC 3 phases 10 hp 575 V AC 3 phases
[Ue] rated operational voltage	600 V AC
Control type	No control units
Local signalling	No indicator
Auxiliary contact composition	Without
Thermal overload type	Melting alloy 3 Thermal Units
Disconnecter device type	Fusible disconnect switch, Type H Fuse, 30 A
NEMA size	1

Environment

NEMA degree of protection	NEMA 1 painted sheet steel and with external reset
---------------------------	--

Offer Sustainability

Sustainable offer status	Not Green Premium product
RoHS (date code: YYWW)	Will not be Compliant

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.